

Electrical Multimeter True RMS 114 - Fluke

Designed for easy one-handed operation, the compact Fluke 114 True RMS Digital Electrical Multimeter is the perfect troubleshooting tool for go/no go testing. Its AutoVolt capability automatically switches to measure AC or DC voltage, whichever is present. The Fluke 114 displays True-RMS voltage and current readings with 6000 count resolution, and tests frequency, continuity and resistance. A large white LED backlight aids work in poorly lit areas. A Fluke 114 multimeters are independently tested for safe use in CAT III 600V environments

Key Features:

- Dimensions: 167mm x 84mm x 46mm
- Weight: 550g
- Operating Temperature: -10 °C to 50 °C
- Includes:
 - Fluke TL75 Test Leads
 - Holster
 - Users Manual
 - Installed 9V Battery
- True RMS measurements
- AutoVolt technology for automatic AC/DC voltage selection
- Large, white, LED backlit display
- Resistance and continuity
- Min/Max/Average records signal fluctuations
- CAT III 600 V safety rated



SKU/Part #
MET-F-114



**Guaranteed.
Tested.
In Stock.**

Product Data Sheet

Standards:

- CAT III 600V

