

Modiewark Electrical Safety Kit 6 1900mm - G.L McGavin

G.L McGavin's Modiewark Electrical Safety Kit contains the original AC non-contact Voltage Tester. Detects voltage without touching the voltage source and informs the operator audibly and visually. Multiple models to detect voltages in a variety of ranges to suit your on-site requirements.

Key Features:

- Frequently purchased Proximity Tester Models:
 - **CIG** - Selectable Voltages: OFF, 240V, 415V, 3.3kV, 6.6kV, 11kV, 22kV, 33kV, 66kV
 - **S7** - Selectable Voltages: OFF, 240V, 2kV, 11kV, 22kV, 33kV, 66kV
 - **S9** - Selectable Voltages: OFF, 240v, 2kV, 11kV, 22kV, 33kV, 66kV, 132kV, 330kV
 - **SEAQ** - Selectable Voltages: OFF, 240V, 3.3kV, 6.6kV, 11kV, 33kV, 66kV, 110kV, 275kV
 - **MWB** - Selectable Voltages: OFF, 240V, 3.3kV, 6.6kV, 11kV, 22kV, 33kV
 - Other models and options are located within the [More Information](#) tab.
 - If you require a Custom product, or other models not listed on the website please enter the relevant information in the cart checkout page under 'Order Notes'.



SKU/Part #	Model
MET-M-ES-KIT-6-CIG	Cig
MET-M-ES-KIT-6-S7	S7
MET-M-ES-KIT-6-S9	S9
MET-M-ES-KIT-6-SEAQ	Seaq
MET-M-ES-KIT-6-OTHER	Other
MET-M-ES-KIT-6-MWB	Mwb
MET-M-ES-KIT-6-CUSTOM	Custom



**Guaranteed.
Tested.
In Stock.**

Product Data Sheet

- Proximity Tester:
 - Size: 23cm x 10cm x 10cm
 - Colour: Orange
 - Weight: 900g
 - Operating Temperature: -10C - 65C
 - Made in Australia
 - Suitable to combine with most insulated sticks
 - Multiple models to detect different voltage ranges
 - Comes with 3 x C batteries to ensure on-site readiness
 - Self test function to verify tester is working appropriately
 - Easy selection wheel to change voltage source detection value
 - Loud 85dB buzzer sound to allow for audible detection of voltage source
 - Bright red detection light allows for visual detection of voltage source in noisy environments
 - Identification of the voltage source detection values from 200mm - 300mm away from the voltage source
- Modiewark Electrical Safety Kit
 - Components to create a hot stick to attach to the Modiewark
 - Modiewark Tester to ensure Modiewark is performing appropriately at higher voltage values
 - Orange rescue carry bag to hold all kit contents





**Guaranteed.
Tested.
In Stock.**

Product Data Sheet

Standards:

- IP63

Kit Contents:

- 1 x Modiewark AC Non-Contact Voltage Tester Of Your Choice
- 1 x Rubber O-Ring Used As A Hand Stopper
- 2 x 1200 mm Extension Stick
- 2 x 700 mm Extension stick
- 1 x Electrical Stick End Cap
- 1 x Sunrise Adaptor
- 1 x PVC Carry Bag Hot Stick 1800 4 Side Pockets
- 1 x Modielive EMF Generator For Testing Modiewark

